

Sigen Energy Gateway



- Multiple Sigen C&I inverters connections supported for micro-grid system
- Seamless switchover, ensuring 0ms load-side disruption
- Built-in bypass circuit for enhanced system reliability
- Supports diesel generator connection & smart control
- Real-time current monitoring with 100ms zero export

Sigen Energy Gateway for Sigen C&I Inverter

Preliminary

Sigen Gateway	C600-B	C1200-B	Units
Grid Connection			
Grid connection type	Three phase		
Nominal AC voltage	380 ~ 400		V
Nominal AC current	912	1,824	A
Nominal AC power	600	1,200	kW
Nominal AC frequency	50 / 60		Hz
Disruption time of backup switch ¹	0		ms
AC Output to Backup Port			
Nominal AC voltage	380 ~ 400		V
Nominal AC current	912	1,824	A
Nominal AC power	600	1,200	kW
Nominal AC frequency	50 / 60		Hz
Overvoltage category	III		
Inverter Connection			
Number of connection ports	10	20	
Nominal AC voltage	380 ~ 400		V
Max. AC input current ²	200 (6 ports), 160 (4 ports)	200 (12 ports), 160 (8 ports)	A
Max. AC power ²	125 (6 ports), 80 (4 ports)	125 (12 ports), 80 (8 ports)	kW
Smart Port Connection			
Generator output voltage	380 ~ 400		V
Nominal AC current	912	1,824	A
Nominal AC power	600	1,200	kW
Generator 2-wire start	Supported		
General Data			
Dimensions (W / H / D)	1,800 / 2,300 / 1,270		mm
Weight	1,100	1,300	kg
Storage temperature range	-40 ~ 70		°C
Operating temperature range ³	-30 ~ 55		°C
Relative humidity range	0% ~ 95%		
Max. operation altitude ³	4,000		m
Cooling	Smart air cooling		
Ingress protection rating	IP20		
Communication	Fast Ethernet, RS485, dry contact		
Installation method	Ground-mounted		

1. This refers to the load-side disruption time, to achieve this functionality Sigen Energy Gateway needs to be used together with Sigen Hybrid Inverter and Sigen Battery. Test conditions: In the open-circuit state of the power grid, the total power of the Sigen Hybrid Inverter is higher than the total power of the backup loads.
2. This series of energy gateway has two types of molded case circuit breakers inside, please refer to the installation guide for their specific mounting locations
3. Please consult Sigenergy for detailed power derating information.

Disclaimer: The information in this file is provided on an "as is" basis. To the fullest extent permitted by law, Sigenergy Technology Co., Ltd. excludes all representations and warranties relating to this file and its contents or which is or may be provided by any affiliates or any other third party, including in